Heat Alarm

10 YEAR LITHIUM CELL POWERED



Model EIB603TYC HEAT Alarm

- Practically eliminates nuisance alarms
- Suitable for Kitchens & areas where smoke alarms may be subjected to nuisance alarms
- Aesthetically pleasing, compact design
- Battery capacity is sufficient to outlast the useful lifespan of the alarm.
- Large Easy to use Test button
- Interconnect up to 12 battery powered alarms
- Easy to fit twist-on base
- Optional upgrade to enable RadioLINK interconnect
- Kitemarked to BS 5446-2:2003
- Certified to AS1603.3
- Manufactured in Ireland to ISO 9001:2000



Product Description

The EIB603TYC alarm is activated by heat from a fire, not smoke, which makes it ideal for kitchen installations where smoke detectors are prone to nuisance alarms.

The EIB603TYC has a 10 Year Lithium battery that is non replaceable.

The EIB603TYC should always be interconnected to other smoke alarms in the dwelling or escape routes to ensure that all occupants are alerted to the danger.

The EIB603TYC modular design allows it to be upgraded for RadioLINK functionality with the addition of an RF module.

Up to 12 battery powered smoke and heat alarms may be linked using hardwire or RF connectivity.

RadioLINK enabled smoke and/or heat alarms can be house coded as a system to prevent communication with other nearby RadioLINK systems.

Operation

- The heat detector will alarm when the temperature reaches 58°C. It will automatically reset and silence the alarm when the temperature drops below this limit.
- The red indicating LED will flash once every 40 seconds to show that the alarm is powered and it has performed an automatic power supply test.
- The built in sounder will provide a minimum sound output of 85dB(A) @ 3m.
- Pressing and holding the "Test" button will check the sensor, electronics and sound the horn.
- The alarm is not powered until it is twisted on the mounting base, thus avoiding battery power consumption during storage and prior to installation.
- When used in a RadioLINK configuration, EIB603TYC heat alarms and other RadioLINK smoke alarms must be house coded. This will avoid interference and interconnection with other RadioLINK systems.
- Keep all doors closed to rooms with heat alarms at night and while premises are unoccupied.



Melbourne

Sydney

Australia Head Office: 4 Pike Street Rydalmere NSW 2116 **Ph**+61 2 9684 1466 **Fx**+61 2 9684 4146 **Toll Free** 1300 78 FIRE

New Zealand Unit 106, The Zone, 23 Edwin Street Mount Eden 1024 **Ph**+64 9 638 4644 **Fx**+64 9 6384645 **Toll Free** 0800 220 007

AUS Web: www.brooks.com.au NZ Web: www.brooks.co.nz

Hobart

E & OE As our policy is one of continuous product development, we reserve the right to alter product details without prior notice.

Brisbane

Perth

Adelaide

EIB603TYC 191110

Model EIB603TYC HEAT Alarm

Technical Specification

Sensor: Fast response thermistor (class

A1) with threshold set to 58°C

Button Test: Pressing the test button tests the

sensor, electronics and horn.

9V supplied by 10 Year Lithium **Battery Voltage:**

Battery with 2,000mAh capacity.

Power-On Indicator: Red LED flashes through cover

every 40 seconds

Alarm Indicator: Red LED flashes rapidly on the

> alarm sensing the fire and the sounder is activated. The sounders on all interconnected alarms are

also activated.

Piezoelectric-horn Alarm:

Alarm Sound Output: 85dB (A) (minimum) @ 3m

Normal Operating

Temperature Range:

Humidity Range: 15% to 95% Relative Humidity

0 to 40°C

(non-condensing)

Hardwire Interconnect up to 12

Interconnect: alarms and remote control devices

RadioLINK Optional Interconnect for up to 12 Interconnect: battery powered RadioLINK ready

alarms and remote control devices

Fixing: Screw fixings supplied

Dimensions: 115mm (diameter) 55mm

(height)

Weight: 200 grams

Warrantv: 5 year (limited) warranty

Compliance: Certified to AS1603.3

Kitemarked to BS 5446-2:2003,

CE approved,

Manufactured to ISO 9001:2000

quality standards.



Melbourne

Adelaide

Sydney

Australia Head Office: 4 Pike Street Rydalmere NSW 2116 Ph+61 2 9684 1466 Fx+61 2 9684 4146 Toll Free 1300 78 FIRE

New Zealand Unit 106, The Zone, 23 Edwin Street Mount Eden 1024 Ph+64 9 638 4644 Fx+64 9 6384645 Toll Free 0800 220 007

Darwin

AUS Web: www.brooks.com.au NZ Web: www.brooks.co.nz

Hobart

EIB603TYC 191110 E & OE As our policy is one of continuous product development, we reserve the right to alter product details without prior notice.

Perth

Brisbane