

CX³ contactors with handle from 16 A to 63 A



4 125 44



4 125 56



Dimensions see **p. 176**
Technical characteristics **p. 170**

Conform to IEC/EN 61095
Space for power supply busbar on top (up to 25 A)

Pack Cat.No. **Power contactors with 24 V~ coil and handle**

Manual override for test and repair function, carried out via the handle
Permanent "ON" or "OFF" without automatic reset

2-pole - 250 V~

	I max	Connection	Type of contact	Number of modules
1	25 A		2 N/O	1
1	40 A		2 N/O	2
1	63 A		2 N/O	2

4-pole - 400 V~

	I max	Connection	Type of contact	Number of modules
1	25 A		4 N/O	2
1	40 A		4 N/O	3
1	63 A		4 N/O	3

Low noise power contactors with 230 V~ coil and handle

2-pole - 250 V~

	I max	Connection	Type of contact	Number of modules
1	25 A		2 N/O	1
1	40 A		2 N/O	2
1	63 A		2 N/O	2

4-pole - 400 V~

	I max	Connection	Type of contact	Number of modules
1	25 A		4 N/O	1
1	40 A		4 N/O	2
1	63 A		4 N/O	2

Pack Cat.No. **Power contactors with 230 V~ coil and handle**

Manual override for test and repair function, carried out via the handle
Permanent "ON" or "OFF" without automatic closing of the contactor

2-pole - 250 V~

	I max	Connection	Type of contact	Number of modules
4	25 A		2 N/O	1
1	40 A		2 N/O	2
1	63 A		2 N/O	2
1	63 A		2 N/C	2

3-pole - 400 V~

	I max	Connection	Type of contact	Number of modules
1	40 A		3 N/O	3
1	63 A		3 N/O	3

4-pole - 400 V~

	I max	Connection	Type of contact	Number of modules
2	25 A		4 N/O	2
1	40 A		4 N/O	3
1	63 A		4 N/O	3
1	63 A		4 N/C	3

NEW

CX³ contactors without handle from 16 A to 63 A

Auxiliaries for CX³ contactors



4 125 23



4 125 35



4 124 29



4 124 31



Dimensions see p. 176
Technical characteristics p. 170

Conform to IEC/EN 61095
Space for power supply busbar on top (up to 25 A)

Pack	Cat.No.	Power contactors with 230 V~ coil			
2-pole - 250 V~					
		I max	Connection	Type of contact	Number of modules
4	4 125 21	16 A		N/C + N/O	1
10	4 125 23	25 A		2 N/O	1
1	4 125 27	63 A		2 N/O	2
1	4 125 24	25 A		2 N/C	1
4-pole - 400 V~					
5	4 125 35	25 A		4 N/O	2
1	4 125 41	63 A		4 N/O	3
1	4 125 36	25 A		4 N/C	2
1	4 125 33	25 A		2 N/C + 2 N/O	2

Pack	Cat.No.	Signalling auxiliaries for contactors			
		Auxiliary changeover switch Used to signal the position status of the contacts on the product to which it is connected			
		For 1 module contactors 16 A to 25 A			
		I max	Voltage	contact	Number of modules
1	4 124 29	5 A	250 V~	N/C + N/O	0.5
		For 2 module contactors 25 A			
		Maximum 2 auxiliary devices per contactor Fitted on left-hand side of contactor			
1	4 124 30	5 A	250 V~	N/C + N/O	0.5
		For 40 and 63 A contactors			
		Maximum 1 auxiliary device per contactor Fitted on left-hand side of contactor			
1	4 124 31	5 A	250 V~	N/C + N/O	0.5

CX³ contactors

■ Technical characteristics

- Rated impulse withstand voltage (Uimp): 4 kV
- Mechanical endurance (no. of operating cycles): 10⁶ cycles
- Operating temperatures: - 25 °C to + 40 °C
- Storage temperatures: - 40 °C to + 70 °C

Contactor protection against short circuits according to standard EN 61095, conditional short-circuit current:

- I_q = 6 kA for 16 to 25 A contactors
- I_q = 3 kA for 40 to 63 A contactors

Circuit breaker or gG fuse rated:

- ≤ 16 A for 16 A rating • ≤ 40 A for 40 A rating
- ≤ 25 A for 25 A rating • ≤ 63 A for 63 A rating

• Consumption of a contactor control coil

16 A and 25 A power contactors					
Coil voltage	24 V~		230 V~ low noise	230 V~	
Current	16 A and 25 A	25 A	25 A	16 A and 25 A	16 A and 25 A
Type of contact	NC + NO 2 NO	4 NO	2 NO	NC + NO 2 NO 2 NC	2 NC + 2 NO 4 NO 4 NC
Dimensions	1 mod.	2 mod.	1 mod.	1 mod.	2 mod.
Holding current	200 mA	300 mA	12 mA	20 mA	20 mA
Inrush current	970 mA	2500 mA	60 mA	90 mA	200 mA

40 A and 63 A power contactors				
Coil voltage	24 V~		230 V~	
Current	40 A and 63 A	40 A and 63 A	40 A and 63 A	40 A and 63 A
Type of contact	2 NO	4 NO	2 NO 2 NC	3 NO 4 NO 4 NC
Dimensions	2 mod.	3 mod.	2 mod.	3 mod.
Holding current	250 mA	270 mA	15 mA	30 mA
Inrush current	1750 mA	1500 mA	150 mA	200 mA

• Recommendations

Insert a spacing module (Cat.No. 4 063 07 p. 150):

- every two contactors when the ambient temperature is below 40 °C
- every contactor when the ambient temperature is between 40 and 60 °C

Contactor rating	40 °C	50 °C	60 °C
I_e = 16 A	16 A	14 A	12 A
I_e = 25 A	25 A	22 A	20 A
I_e = 40 A	40 A	36 A	32 A
I_e = 63 A	63 A	57 A	50 A

• Max. connection cross-section in mm²

Conductor type	Ratings ≤ 25 A	Ratings 40 & 63 A
Rigid	6 ² or 2 x 2,5 ²	25 ² or 2 x 10 ²
Flexible	6 ² or 2 x 2,5 ²	25 ² or 2 x 10 ²
Flexible with single end cap	6 ²	16 ²
Flexible with double end cap	2 x 4 ²	2 x 16 ²

■ Contactor selection charts

• Incandescent lamps

Tungsten and halogen filaments 230 V~								
Nominal wattage	40 W	60 W	75 W	100 W	150 W	200 W	500 W	1000 W
16 A	45	30	24	19	13	10	4	2
25 A	60	48	38	30	20	15	6	3
40 A	96	77	61	48	32	24	10	5
63 A	154	123	97	77	51	38	15	8

ELV halogen bulbs with ferromagnetic ballast							ELV halogen bulbs with electronic ballast						
Nominal wattage	20 W	35 W	50 W	75 W	100 W	150 W	20 W	35 W	50 W	75 W	100 W	150 W	
16 A	32	20	15	12	9	6	60	40	28	18	14	9	
25 A	52	30	24	16	12	8	80	50	40	26	20	13	
40 A	68	39	31	21	16	10	112	70	56	36	28	18	
63 A	88	51	41	27	20	14	157	98	78	51	39	25	

■ Contactor selection charts (continued)

• Fluorescent tubes with ferromagnetic ballast

Single parallel compensated fluorescent						Double series compensated fluorescent				
Nominal wattage	18 W	20 W	36 W	58 W	115 W	2 x 20 W	2 x 36 W	2 x 40 W	2 x 58 W	2 x 140 W
16 A	24	24	16	11	5	30	24	22	15	6
25 A	33	30	25	17	9	45	38	35	24	10
40 A	43	39	33	22	12	68	57	53	36	15
63 A	56	51	42	29	15	101	86	79	54	23

Quadruple series compensated fluorescent					Compact fluorescent with built-in starter			
Nominal wattage	4 x 18 W				7 W	10 W	18 W	26 W
16 A	16				50	40	28	19
25 A	24				60	50	42	28
40 A	36				78	65	55	36
63 A	54				101	85	71	47

• Fluorescent tubes with electronic ballast

Single fluorescent					Double fluorescent		
Nominal wattage	18 W	30 W	36 W	58 W	2 x 18 W	2 x 36 W	2 x 58 W
16 A	72	42	36	22	36	20	12
25 A	110	68	58	36	56	30	19
40 A	165	102	87	54	84	45	29
63 A	248	153	131	81	126	68	43

Triple fluorescent (series compensated)				Quadruple fluorescent (series compensated)	
Nominal wattage	3 x 14 W	3 x 18 W	4 x 14 W	4 x 18 W	
16 A	34	26	26	20	
25 A	46	38	37	28	
40 A	62	51	52	39	
63 A	84	69	73	55	

Compact fluorescent with built-in electronic power supply					
Nominal wattage	7 W	11 W	15 W	20 W	23 W
16 A	120	80	64	50	43
25 A	200	125	90	70	60
40 A	280	175	126	98	84
63 A	392	245	176	137	118

• Discharge lamps with compensation

Metal halogenide							Low pressure sodium vapour					
Nominal wattage	35 W	70 W	100 W	150 W	250 W	400 W	18 W	35 W	55 W	90 W	135 W	180 W
16 A	10	6	5	3	2	1	12	6	5	3	2	2
25 A	15	9	7	5	3	2	20	10	7	5	3	3
40 A	23	14	11	8	5	3	30	15	11	8	5	5
63 A	34	20	16	11	7	5	45	23	16	11	7	7

High pressure sodium vapour						High pressure mercury vapour				
Nominal wattage	70 W	150 W	250 W	400 W	1000 W	50 W	80 W	125 W	250 W	400 W
16 A	8	7	5	3	1	11	8	6	3	2
25 A	10	9	6	4	2	15	10	8	4	3
40 A	15	14	9	6	3	21	14	11	6	4
63 A	23	20	14	9	5	29	20	16	8	6

High pressure mixed				
Nominal wattage	100 W	160 W	250 W	400 W
16 A	9	6	4	2
25 A	11	7	5	3
40 A	14	9	7	4
63 A	19	12	8	5