## CLEVERTRONICS 240V ARGONAUT QUANTUM LED WEATHERPROOF BATTEN WITH MICROWAVE SENSOR & SWITCHABLE COLOUR



PRODUCT INFORMATION				
Part Number	ARGO-1200-SEN			
MIC	AUB04620370001			
Description	240V Argonaut Quantum 1200mm Weatherproof Batten Batten with Microwave Sensor (Hi/Lo) and Switchable Colour			
Construction	Polycarbonate Base, Polycarbonate Diffuser and Captive Stainless Steel Clips (SS301)			
Mounting	Surface mount			
Dimensions L x W x H	1265mm x 88mm x 121mm			
Weight	2.4 kg			
Diffuser	Polycarbonate			
Driver / Ballast	LED Driver – Merytek MLC65C			
Lamp(s)	Dual LED strip module, 3,000K warm white, 5,700K cool white, 50,000h life [L70/B50 Ta 40°C], Ra>80			
Operating Voltage	240V AC; 50Hz			
Power Factor	0.85			
Supply Current	190mA +/- 20mA			
Total lumen output	see table on page 2			
Power Consumption	see table on page 2			
IP Rating	IP65			
Operating Temperature	0°C to 40°C			
Impact Rating	IK08			
Alternate Part Number	F4WB-MS-HL			

REPLACEMENT PARTS		
PART NUMBER	DESCRIPTION	
1330079	LED HL Driver - MLC65C-P8	

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order



## Power consumption at 650mA setting:

Colour	Standby Lamp ON	Standby Lamp ON MIN @ 10%
3000K	37 W	5.7 W
4000K	34 W	5.7 W
5700K	36 W	5.8 W

## Lumen Output at 650mA setting:

Colour	Lumen Output
3000K	3684 lm
4000K	4060 lm
5700K	3732 lm